

**KOHLER**®



## HX 7500 T C5

PORTABLE POWER

Generating Sets Range INTENS

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen commitment to safety and quality.

## HX 7500 T C5

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	5.70
Max power (kVA)	7.10
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1.10

### ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	80

### PACKAGING

Packaging type	Box
Length (cm)	78.50
Width (cm)	58
Height (cm)	59.50
Weight (kg)	82.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	505

### ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

### OPTIONS



**R03**

This set includes the hour meter and the differential circuit breaker.



**RKB2**

Trolley kit for the generating sets superior to 6kW



**R19**

Maintenance kit for Honda GX390 engines (except Alizé 6000E and Alizé 7500 TE)



**RH1**

Cover for SDMO 's generating sets, welding sets and water pumps



**RPM**

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V